

CHINA DELLENT

CE/ISO9001

Three Phase Diesel Generator 150kVA 120kW Cummins Diesel Genset With Soundproof Canopy

Basic Information

- Place of Origin:
- Brand Name:
- Certification:
- Model Number:
- Minimum Order Quantity:
- Price:

Our Product Introduction

- Packaging Details:
- Delivery Time:
- Supply Ability:
- DE-C165 1 pc bargain face-to-face PLASTIC WRAP OR PLYWOOD CASE 20-30 DAYS 1 MONTH 600PCS



DELLEN

Product Specification

- Name:
- Engine Brand:
- Engine Model:
- Prime Power:
- Standby Power:
- Frequency:
- Fuel Type:
- Noise Level:
- Speed:
- Warranty:
- Cooling System:
- Highlight:

Cummins
6BTAA5.9-G12
150kVA 120kW
165kVA 132kW
50Hz
Diesel
75dBA At 7M
1500rpm
12 Months/1000 Hours
Water-Cooling System
Three Phase Diesel Generator 150kVA, 120kW Cummins Diesel Genset, 120 kw cummins generator

Cummins Diesel Genset

Three Phase 150kVA 120kW Cummins Diesel Genset Equip With Soundproof Canopy

Engine Specification		
Engine Manufacturer		Dongfeng Cummins Engine Co., Ltd.
Engine Brand		Cummins
Engine Model		6BTAA5.9-G12
No. of Cylinder		6 Cylinder in line
Aspiration		Turbocharged and Air to Air Aftercooled
Governor		Electric
Engine Max. Output Power	kW	154
Displacement	L	5.9
Compression Ratio		17.3 : 1
Starting Voltage	V	24
Bore	mm	102
Stroke	mm	120
Lubrication Oil Capacity	L	16.4
Intake Air Flow	M3/Min	7.6
Fuel Consumption at 100% Load	L/H	34
Alternator Specification		
Alternator Manufacturer		Fuan Dellent Electric & Machinery Co., Lt
Alternator Brand		DELLENT

Alternator Manufacturer	
Alternator Brand	
kVA	150
Hz	50Hz
М	≤1000
Insulation	
Phase	
Working Temperature without power decrease	
Working Altitude without power decrease	
Automatic Voltage Regulation	
Protection Grade	
	Hz M ecrease

Control Panel Specification		
Controller Brand	Deepsea	
Controller Model	DSE6120	
Breaker Brand	Delixi	
Breaker Capacity (A)	250	
Battery Charger	Smartgen Model BAC06A	
Emergency Stop Button	Supply	
Automatic Mains Fail (AMF)	Supply	

Fuel Level	Supply
Automatic Transfer Switch	ATS as optional part
generator include Start-up fault (genera and generator set shutdown), Low oil pr	ion with alarm and shutdown of the diesel tor set shutdown), High coolant temperature (alarm ressure (alarm and generator set shutdown), Low I alarm (as optional), Overload (alarm and e high (alarm).
Optional controller: Each model of Deep	osea, Smartgen, ComAp brand controller.
. Why Choose Us:	
Dedicated	s' need.
Enthusiasm	
We respond to our Customers' ENTHU	
We cherish our Customers' LOYALTY	
We aim to establish our own LUXURY	brand
Efficient	
We offer our EFFICIENT service	
tewest	



We strive for winning the TRUST from Customers

. QUALIFICATION CENTIFICATE:



. FACTORY INTERIOR:



NO.7, JINYE ROADTIEHU INDUSTRIAL AREA CHENGYANG TOWN, FUAN CITY, NINGDECITY, FUJIAN.CHINA